



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

## Model #: OMNISMART1400

### OmniSmart 1400VA Tower Line-Interactive 120V UPS with USB port



#### Highlights

- 1400VA / 1.4kVA tower 120V line interactive UPS
- Corrects brownouts and overvoltages from 75V to 147V
- USB port, Front panel status LEDs
- NEMA 5-15P input plug and 6 NEMA 5-15R outlets

#### Description

Tripp Lite's OMNI SMART 1400 line interactive UPS system offers voltage regulation, surge suppression and long lasting battery support for personal computers, internetworking equipment and other sensitive electronics. Supports a single entry level PC system for up to 75 minutes during power failures to facilitate a safe shutdown without data loss. Automatic Voltage Regulation (AVR) circuits regulate brownouts as low as 75 volts and overvoltages to 147 volts back to normal 120V levels, all without using battery power. Includes 6 battery supported outlets and 6 foot AC line cord. USB port enables optional safe unattended system shutdown in the case of extended power failure as well as continuous UPS and site power condition monitoring, USB cable included. PowerAlert software available via free download from [www.tripplite.com](http://www.tripplite.com). Built-in audible alarm and 5 front panel LEDs indicate status of line power, battery power, battery low/replace, voltage regulation and overload. 1400VA/940 watt power handling ability supports multiple entry-level PCs, network workstations, point-of-sale terminals, small to medium business phone systems, audio/video workstations and heavily configured home theater systems. Offers 8 minutes battery runtime with a full load of 1400VA and 24 minutes with a half load of 700VA. Supports hot swap battery replacement via built-in access panel. \$200,000 [connected equipment insurance](#) (USA and Canada Only).

#### Package Includes

- OMNI SMART 1400 UPS System
- USB cable
- Warranty information
- Instruction manual

#### Features

- OMNI SMART 1400 line interactive UPS system offers voltage regulation and battery support, plus complete AC and dialup/DSL modem line surge suppression
- Prevents equipment damage, data loss and downtime due to power problems
- Supports a single entry level PC system for up to 75 minutes during power failures to enable a safe system shutdown
- Supports a max load of 1400VA for 8 minutes
- Supports a half load of 700VA for 24 minutes
- Automatic Voltage Regulation (AVR) circuits correct brownouts as low as 75 and overvoltages as high as 147 volts back to normal 120 volt levels without using battery power
- Upright tower configuration uses only 66 square inches of floor or desktop space
- Includes 6 battery supported outlets, 6 foot AC line cord (all NEMA 5-15)

- USB port enables safe unattended shutdown without data loss during extended power failures, includes USB cable
- USB port supports messaging of UPS and line power status, including on-battery, low-battery, power-restored, AC line voltage, DC battery voltage and battery capacity
- USB interface supports timed inverter shutoff after unattended shutdown, activate self-test and 10 second reboot of connected equipment
- PowerAlert UPS monitoring software available via free download from [www.tripplite.com](http://www.tripplite.com)
- Supports Tripp Lite's WatchDog software application to restore unresponsive programs by automatically restarting them and rebooting completely locked computers by automatically switching UPS power off and back on again
- Built-in audible alarm and 5 front panel LEDs indicate status of line power, battery power, battery low/replace, voltage regulation and overload status
- 1400VA/940 watt power handling ability supports multiple entry-level PCs, network workstations, point-of-sale terminals, small to medium business phone systems, audio/video equipment stations and heavily configured home theater systems
- Supports hot-swap battery replacement via built-in battery access panel
- Compatible with 120V/60Hz applications for USA, Canada, Mexico and more
- \$200,000 [connected equipment insurance](#) (USA and Canada Only)

## Specifications

OUTPUT	
Output Volt Amp Capacity (VA)	1400
Output kVA capacity (kVA)	1.4
Output Watt Capacity (watts)	940
Nominal Output Voltage(s) Supported	115V; 120V
Frequency compatibility	60 Hz
Output voltage regulation (line mode)	-18%, +8%
Output voltage regulation (Battery mode)	115V (+/- 5%)
Built-in UPS output receptacles	6 5-15R outlet(s)
Basic PDU options	<a href="#">PDU1215</a> (1U / 13 5-15R outlets); <a href="#">PDUNV</a> (1U / 2 C19, 12 C13 outlets); <a href="#">PDU1415</a> (0U / 14 5-15R outlets); <a href="#">PDUV15</a> (0U / 12 5-15R outlets)
Metered PDU options	<a href="#">PDMH15</a> (1U / 13 5-15R outlets); <a href="#">PDMH15AT</a> (1U / 8 5-15R outlets)*; <a href="#">PDUMV15</a> (0U / 16 5-15R outlets)
Switched PDU options	<a href="#">PDMH15ATNET</a> (1U / 8 5-15R outlets)*; <a href="#">PDUMV15NET</a> (0U / 16 5-15R outlets)
External PDU redundancy options	*Auto Transfer Switch features utilizing the secondary PDU input cord are compatible with Smart Online UPS models only
Output AC waveform (AC mode)	Sine wave
Output AC waveform (battery mode)	PWM sine wave
INPUT	
Rated input current (at maximum load)	9.2A
Nominal Input Voltage(s) Supported	120V AC
UPS input connection type	5-15P
UPS Input cord length (ft.)	6

UPS Input cord length (m)	1.8
Recommended Electrical Service	15A 120V
Input cord length (ft.)	6
Input cord length (m)	1.8
<b>BATTERY</b>	
Full load runtime (minutes)	8 min. (940w)
Half load runtime (minutes)	24 min. (470w)
DC system voltage (VDC)	36
Battery recharge rate (included batteries)	Less than 8 hours from 10% to 90%
Replacement battery cartridge (internal UPS battery replacement)	RBC53
Battery Access	Battery access door
<b>VOLTAGE REGULATION</b>	
Voltage regulation description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 75 to 147
Overvoltage correction	Input voltages between 128 and 147 are reduced by 12%
Undervoltage correction	Input voltages between 93 and 107 are boosted by 14%
Severe undervoltage correction	Input voltages between 75 and 92 are boosted by 30%
<b>LEDS ALARMS &amp; SWITCHES</b>	
LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status
Alarms	Audible alarm indicates power-failure and low-battery conditions
Alarm cancel operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation
<b>SURGE / NOISE SUPPRESSION</b>	
UPS AC suppression joule rating	480
UPS AC suppression response time	Instantaneous
EMI / RFI AC noise suppression	Yes
AC suppression joule rating	480
AC suppression response time	Instantaneous
<b>PHYSICAL</b>	
Installation form factors supported with included accessories	Tower

Installation form factors supported with optional accessories	Wallmount (UPSWM - tower mounting kit)
Primary form factor	Tower
UPS / Power Module dimensions in primary form factor (height x width x depth / inches)	12.8 x 7.5 x 9.2
UPS / Power Module dimensions in primary form factor (height x width x depth / cm)	32.4 x 19 x 23.5
UPS / Power Module weight (lbs)	36.4
UPS / Power Module weight (kg)	16.5
UPS Shipping dimensions (height x width x depth / inches)	18.2 x 12 x 13.8
UPS Shipping dimensions (height x width x depth / cm)	46.4 x 30.5 x 34.9
Shipping weight (lbs)	40
Shipping weight (kg)	18.2
UPS housing material	PVC
<b>ENVIRONMENTAL</b>	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
AC mode BTU / hr. (full load)	204
Battery mode BTU / hr. (full load)	277.9
<b>COMMUNICATIONS</b>	
Communications interface	USB
PowerAlert software	Free download from <a href="http://www.tripplite.com">www.tripplite.com</a>
Communications cable	USB cable included
WatchDog compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
<b>LINE / BATTERY TRANSFER</b>	
Transfer time	2-4 milliseconds
Low voltage transfer to battery power (setpoint)	75
High voltage transfer to battery power (setpoint)	147

<b>SPECIAL FEATURES</b>	
<b>Cold Start (startup in battery mode during a power failure)</b>	Cold-start operation supported
<b>Green &amp; high efficiency features</b>	Greater than 95% efficiency - GREEN UPS
<b>CERTIFICATIONS</b>	
<b>UPS Certifications</b>	Tested to UL1778 (USA); Tested to CSA (Canada); Tested to NOM (Mexico); Meets FCC Part 15 Category B (EMI)
<b>WARRANTY</b>	
<b>Product Warranty Period (Worldwide)</b>	2-year limited warranty
<b>Connected Equipment Insurance (U.S., Canada &amp; Puerto Rico)</b>	\$200,000 <a href="#">Ultimate Lifetime Insurance</a>

## Related Items

### Optional Products

Related Model	Description	Qty.
<a href="#">DCATV</a>	Network Surge Suppressor - Essential protection for TV/VCR coaxial lines	1
<a href="#">DNET1</a>	Network Surge Suppressor - Essential protection for data and communication lines	1
<a href="#">DTEL2</a>	Network Surge Suppressor - Essential protection for data and communication lines	1
<a href="#">UPSWM</a>	Wallmount Bracket and installation accessories (4 washers, 4 screws, 1 Velcro safety strap)	1
<a href="#">WEXT3-OMNI</a>	3-Year Extended Warranty - For OmniSmart, OmniPro, OmniVS	1
<a href="#">WEXT5-OMNI</a>	5-Year Extended Warranty - For OmniSmart, OmniPro, OmniVS	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?variables.txtModelID=18](http://www.tripplite.com/en/products/model.cfm?variables.txtModelID=18).

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.