

Model #: SMART5000TEL3U

SmartPro 5kVA Line Interactive Sine Wave UPS, SNMPWEBCARD option, 3U Rack/Tower, USB, Serial, EPO, 208V

Highlights

- 5kVA / 5000VA line interactive 3U rack/tower UPS; Sine wave output
- 208V nominal output during inputs of 174-282V; Supports 600VA 120V output
- USB, Serial, EPO & optional SNMP/Web card monitoring options
- 95% line-mode efficiency; Hot-swappable internal batteries
- NEMA L6-30P input; 2 NEMA 5-15R, 2 L6-20R & 1 L6-30R outlets



Description

Tripp Lite's SMART5000TEL3U intelligent, line interactive UPS protects server, networking and telecommunications equipment from blackouts, voltage fluctuations and surges in a compact rackmount housing. Completely self-contained UPS system occupies only 3 rack spaces (3U) in a standard 19 inch rack, making this model one of the smallest 5kVA UPS systems available. Included accessories support mounting 4 post rack enclosures. Large capacity 5000 VA/3750 watt UPS system accepts raw 208/240V AC input, adjusting output to normal 208V levels. One pair of 120V outlets support up to 600VA monitors and other low voltage accessories. Includes slot for internal SNMP/web card, plus 2 DB9 and 2 USB enhanced monitoring ports for unattended shutdown, remote control and monitoring of UPS system and power data. Five outlets (two L6-20R, one L6-30R and two 5-15R) allow the connection of high current 20 and 30 amp 208V connectors and up to two 120V devices (max 600VA at 120V).

Package Includes

- SMART5000TEL3U UPS System
- PowerAlert Software and cabling
- Mounting hardware
- Instruction manual

Features

- Large 5000VA/3750-watt output capacity accommodates solitary large loads or multiple low-power loads
- High power density 5kVA power module occupies only 3 rack spaces (3U)
- 16 minutes half-load runtime (with a continuous load 2500VA; much longer runtime available at smaller loads)
- . Line-interactive voltage regulation corrects severe brownouts and overvoltages without using battery power
- High voltage output supports 208V server, internetworking and telecom applications
- Pair of 120V outlets supports up to 600VA for standard 120V monitors, voicemail and other low-power networking devices
- Five total outlets (two L6-20R, one L6-30R and two 5-15R)
- Diagnostic LEDs provide visual indication of 17 separate performance conditions
- Included PowerAlert Software provides e-mail or pager notification of power problems and simultaneous automatic unattended shutdown of multiple servers
- 4 built-in communications ports (2 USB/2 DB9) for remote monitoring and unattended shutdown
- Slot for SNMP/web card (part#: SNMPWEBCARD) and environmental sensor (part#: ENVIROSENSE) for remote communications in large IP environments
- Emergency Power Off (EPO) interface for emergency shutoff in large facilities
- Hot-swappable/user-replaceable batteries allow on-site battery replacement through the front panel without powering off connected equipment or removing the UPS from the rack
- UPS ships fully assembled and ready for installation; no time-consuming user battery connections required

Specifications

Output Volt Amp Capacity (VA) 5000 Output VAI capacity (KVA) 5 Output WKI Capacity (Vats) 3750 Output WKI Capacity 3.8 Output WKI capacity 3.8 Output WKI capacity 0.8 Nominal Output Voltage(s) 120V: 208V Supported 120V output Is limited to 600V/A / 450 watts (maximum) Frequency compatibility 60 Hz Output Voltage details 120V output Is limited to 600V/A / 450 watts (maximum) Frequency compatibility 60 Hz Output Voltage regulation (Battery mode) 28-8 120V (-6%, +20%) Output voltage regulation (Battery mode) 1-5% Dutput Voltage regulation (Battery mode) 1-5% Output voltage regulation (Battery mode) 12-15R outlet(s): 2.18-20R outlet(s): 1.18-30R outlet(s) Output receptacle details 120V 5-15R outlets are limited to 600V/A / 450 watts (maximum) Output voltage regulation (Battery mode) Sine wave Output AC waveform (AC Rotage beta bracker supports L6-20R outlets, 5A breaker supports L6-30R outlets is line wave Output AC waveform (AC Rotage beta bracker supports) Sine wave INPUT 10	OUTPUT	
(YA)Image: Constant of Consta		
Quiput Watt Capacity 3750 Output Wat capacity 3.8 Output Wat capacity 3.8 Output Power factor 0.8 Nominal Output Voltaged 120V; 208V Nominal Output Voltaged 120V output is limited to 600VA /450 watts (maximum) Frequency compatibility 60 Hz Output Voltage regulation 208 & 120V (6%, +20%) Output voltage regulation 25-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation 25-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation 20V 5-15R outlet(s); 2 L6-20R outlet(s); 5 A breaker supports 5-15R outlets, L6-30R outlet(s) Output voltage regulation 200 Adoube pole breaker supports L6-20R outlets, 5 A breaker supports 5-15R outlets, L6-30R outlet is Output Ac waveform (AC Sine wave Output Ac waveform (AC 24 Adoube pole breaker supports L6-20R outlets, 5 A breaker supports 5-15R outlets, L6-30R outlet is Nominal Input Voltage(s) 24 Adoube pole breaker supports L6-20R outlets, 5 A breaker supports 5-15R outlets, L6-30R outlet is Nordshort 5 Breakered 204 output breakered Nordshort 24 Adoube pole breaker supports L6-20R outlets, 5 A breaker supports 5-15R outlets, L6-30R output is <th></th> <td>5000</td>		5000
(wats)Image: Image:	Output kVA capacity (kVA)	5
Output Poilting 0.8 Supported 120V: 208V Nominal Uptut Voltage(s) 120V output Is limited to 600VA / 450 watts (maximum) Frequency compatibility 60 Hz Output voltage regulation 208 & 120V (-6%, +20%) Output voltage regulation 20-515R outlet(s): 2.16-20R outlet(s): 1.16-30R outlet(s) Output voltage regulation 25-15R outlet(s): 2.16-20R outlet(s): 1.16-30R outlet(s) Output voltage regulation 120V 5-15R outlet are limited to 600VA / 450 watts (maximum) Output voltage regulation 120V 5-15R outlet are limited to 600VA / 450 watts (maximum) Output voltage regulation 120-515R outlet are limited to 600VA / 450 watts (maximum) Output developed to details 120-V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output developed to details 120-V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output developed to details 120-V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output voltage regulation 20-50 coutlet are limited to 600VA / 450 watts (maximum) Output developed to eaker supports L6-20R outlets, SA breaker supports 5-15R outlets, L6-30R outlet is unbreakered Output Ac waveform (AC Sine wave Output Ac waveform (AC Sine wave <th></th> <td>3750</td>		3750
Nominal Output Voltage(s) 120V; 208V Nominal Voltage details 120V output is limited to 600VA / 450 watts (maximum) Frequency compatibility 60 Hz Output voltage regulation 2088 & 120V (-6%, +20%) Qutput voltage regulation +- 5% Bailt-In UPS output 2 5-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation +- 5% Built-In UPS output 2 5-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation +- 5% Built-In UPS output 2 5-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation iubreakers supports L6-20R outlet(s); 3 L6-30R outlet(s) Output voltage regulation 2 040 double pole breaker supports L6-20R outlets, 5A breaker supports 5-15R outlets, L6-30R outlet is unbreakers outports for the supports 5-15R outlets, L6-30R outlet is unbreakers output servers Output AC waveform (AC Sine wave Output Voltage(s) Supported Supported 2 4A Nominal Input Voltage(s) 2 80V AC Singenered Leictricat 30 A 208V PS Input cord length (ft.) 10 Output voltage (VDC) 43	Output kW capacity	3.8
Supported Indext of the second s	Output power factor	0.8
Frequency compatibility 60 Hz Output voltage regulation 208 & 120V (.4%, +20%) Output voltage regulation +/-5% Output voltage regulation +/-5% Built-in UPS output 25-15R outlet(s); 2.16-20R outlet(s); 1.16-30R outlet(s) Output receptace details 120V 5-15R outlet are limited to 600VA / 450 watts (maximum) Output circuit breaker 20A double pole breaker supports L6-20R outlets, 5A breaker supports 5-15R outlets, L6-30R outlet is Output AC waveform (AC Sine wave Output AC waveform (AC Sine wave Netter mode) Pure Sine wave Numinal Input Voltage(s) 208V AC Supported 6-30P UPS Input cord length (h.) 10 PIS Input cord length (h.) 30A 208V Service 30A 208V Battery recharge ret 5.5 min. (3750w)	Nominal Output Voltage(s) Supported	120V; 208V
Output voltage regulation (line mode) 208 & 120V (-6%, +20%) Output voltage regulation (Battery mode) +/- 5% Built-in UPS output receptacles 2 5-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s) Output voltage regulation 120V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output receptacle details 120V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output circuit breaker 20A double pole breaker supports L6-20R outlets, 5A breaker supports 5-15R outlets, L6-30R outlet is unbreakered Output AC waveform (AC mode) Sine wave Output AC waveform (MC mode) Sine wave Numinal Input Voltage(s) 24A 208V AC 208V AC UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 3 Battery FU Sin (3750w) Full lead runtime (minutes) 8.5 min. (3750w) Battery recharge rate Less than 4 hours from 10% to 90%	Nominal Voltage details	120V output is limited to 600VA / 450 watts (maximum)
(Ine mode) Image: A for a	Frequency compatibility	60 Hz
(Battery mode) Image: Comparison of the state of the sta		208 & 120V (-6%, +20%)
receptacies Characteristic Output receptacie details 120V 5-15R outlets are limited to 600VA / 450 watts (maximum) Output circuit breaker 20A double pole breaker supports L6-20R outlets, 5A breaker supports 5-15R outlets, L6-30R outlet is unbreakered Output AC waveform (AC mode) Sine wave Pure Sine wave Pure Sine wave INPUT Rated input current (at maximum load) Nominal Input Voltage(s) 208V AC Supported 208V AC UPS Input connection type L6-30P UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 3 BATERY Solo 208V Full load runtime (minutes) 8.5 min. (3750w) Half load runtime (minutes) 2.5 min. (3750w) BATERY 20 min. (1875w)	Output voltage regulation (Battery mode)	+/- 5%
Output circuit breaker 20A double pole breaker supports L6-20R outlets, 5A breaker supports 5-15R outlets, L6-30R outlet is unbreakered Output AC waveform (AC mode) Sine wave Output AC waveform (battery mode) Pure Sine wave INPUT Pure Sine wave Rated input current (at maximum load) 24A Nominal Input Voltage(s) supported 208V AC UPS input connection type L6-30P UPS Input cord length (ft.) 10 INPUT 3 Recommended Electrical service 30A 208V EATTERY 8.5 min. (3750w) Half load runtime (minutes) 8.5 min. (3750w) Battery recharge rate Less than 4 hours from 10% to 90%		2 5-15R outlet(s); 2 L6-20R outlet(s); 1 L6-30R outlet(s)
unbreakered unbreakered Output AC waveform (AC mode) Sine wave Output AC waveform (battery mode) Pure Sine wave INPUT Pure Sine wave Rated input current (at maximum load) 24A Nomial Input Voltage(s) 208V AC Supported L6-30P UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 3 Recommended Electrical sol 30A 208V 30A 208V Evervice 8.5 min. (3750w) Half load runtime (minutes) 8.5 min. (3750w) Half load runtime (minutes) 48 Battery recharge rate Less than 4 hours from 10% to 90%	Output receptacle details	120V 5-15R outlets are limited to 600VA / 450 watts (maximum)
mode) Import Output AC waveform (battery mode) Pure Sine wave INPUT Import Current (at maximum load) Rated input current (at maximum load) 24A Nominal Input Voltage(s) Supported 208V AC UPS input connection type L6-30P UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 3 Recommended Electrical Service 30A 208V EATTERY 5.5 min. (3750w) Half load runtime (minutes) 6.5 min. (3750w) Battery recharge rate Less than 4 hours from 10% to 90%	Output circuit breaker	
(battery mode) Intervent (at maximum load) Rated input current (at maximum load) 24A Nominal Input Voltage(s) 208V AC Supported 208V AC UPS input connection type L6-30P UPS Input cord length (ft.) 10 UPS Input cord length (ft.) 3 Recommended Electrical Service 30A 208V EATTERY Event (18750w) Half load runtime (minutes) 8.5 min. (3750w) Battery recharge rate Less than 4 hours from 10% to 90%		Sine wave
Rated input current (at maximum load)24ANominal Input Voltage(s) Supported208V ACUPS input connection typeL6-30PUPS Input cord length (ft.)10UPS Input cord length (m)3Recommended Electrical Service30A 208VBATTERY10Full load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)DC system voltage (VDC)48Battery recharge rateLess than 4 hours from 10% to 90%		Pure Sine wave
maximum load)Nominal Input Voltage(s) Supported208V ACUPS input connection typeL6-30PUPS Input cord length (ft.)10UPS Input cord length (m)3Recommended Electrical Service30A 208VBATTERY5.5 min. (3750w)Full load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)Battery recharge rateLess than 4 hours from 10% to 90%	INPUT	
SupportedUPS input connection typeL6-30PUPS input cord length (ft.)10UPS input cord length (m)3Recommended Electrical Service30A 208VBATTERY3Full load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)DC system voltage (VDC)48Battery recharge rateLess than 4 hours from 10% to 90%		24A
UPS Input cord length (ft.)10UPS Input cord length (m)3Recommended Electrical Service30A 208VBATTERY8.5 min. (3750w)Full load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)DC system voltage (VDC)48Battery recharge rateLess than 4 hours from 10% to 90%	Nominal Input Voltage(s) Supported	208V AC
UPS Input cord length (m) 3 Recommended Electrical Service 30A 208V BATTERY 30A 208V Full load runtime (minutes) 8.5 min. (3750w) Half load runtime (minutes) 20 min. (1875w) DC system voltage (VDC) 48 Less than 4 hours from 10% to 90%	UPS input connection type	L6-30P
Recommended Electrical Service30A 208VBATTERYFull load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)DC system voltage (VDC)48Battery recharge rateLess than 4 hours from 10% to 90%	UPS Input cord length (ft.)	10
Service BATTERY Full load runtime (minutes) 8.5 min. (3750w) Half load runtime (minutes) 20 min. (1875w) DC system voltage (VDC) 48 Battery recharge rate Less than 4 hours from 10% to 90%	UPS Input cord length (m)	3
Full load runtime (minutes)8.5 min. (3750w)Half load runtime (minutes)20 min. (1875w)DC system voltage (VDC)48Battery recharge rateLess than 4 hours from 10% to 90%		30A 208V
Half load runtime (minutes) 20 min. (1875w) DC system voltage (VDC) 48 Battery recharge rate Less than 4 hours from 10% to 90%	BATTERY	
DC system voltage (VDC) 48 Battery recharge rate Less than 4 hours from 10% to 90%	Full load runtime (minutes)	8.5 min. (3750w)
Battery recharge rate Less than 4 hours from 10% to 90%	Half load runtime (minutes)	20 min. (1875w)
Battery recharge rate (included batteries) Less than 4 hours from 10% to 90%	DC system voltage (VDC)	48
	Battery recharge rate (included batteries)	Less than 4 hours from 10% to 90%

Replacement battery cartridge (internal UPS battery replacement)	RBC94-3U (quantity 3)
Battery Access	Front panel battery access door
Battery replacement description	Hot-swappable, user replaceable batteries
VOLTAGE REGULATION	
Voltage regulation description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 167 to 260
Overvoltage correction	Input voltages between 228V and 260V are reduced by 12%
Undervoltage correction	Input voltages between 167V and 194V are boosted by 12%
LEDS ALARMS & SWITCHES	
LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status
Alarms	Audible alarm indicates power-failure, overload and low-battery conditions
Alarm cancel operation	Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status
Switches	2 Switches control off/on power status and alarm-cancel/self-test operation
SURGE / NOISE SUPPRESSIO	N
UPS AC suppression joule rating	1020
UPS AC suppression response time	Instantaneous
EMI / RFI AC noise suppression	Yes
PHYSICAL	
Installation form factors supported with included accessories	4 post 19 inch rackmount (mounting rail kit included)
Installation form factors supported with optional accessories	2 post rackmount (2POSTRMKITWM); Tower (2-9USTAND)
Primary form factor	Rackmount
UPS / Power Module dimensions in primary form factor (height x width x depth / inches)	5.2 x 17.5 x 25
UPS / Power Module dimensions in primary form factor (height x width x depth / cm)	13.3 x 44.4 x 63.5
Installed whole system total rack space height (rack spaces)	3U
Secondary form factor	Tower (requires 2-9USTAND)
Installed whole system dimensions in secondary form factor (height x width x depth / inches)	17.5 x 5.2 x 25

UPS dimensions in secondary form factor (height x width x depth / cm)	44.4 x 13.3 x 63.5
UPS / Power Module weight (lbs)	143.3
UPS / Power Module weight (kg)	65.1
UPS Shipping dimensions (height x width x depth / inches)	11.2 x 23 x 31.5
UPS Shipping dimensions (height x width x depth / cm)	28.6 x 58.4 x 80
Shipping weight (lbs)	181.9
Shipping weight (kg)	82.6
UPS housing material	Steel
Cooling method	Fan
Installed whole system dimensions in secondary form factor (height x width x depth / cm)	44.45 x 13.21 x 63.5
ENVIRONMENTAL	
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius
Relative Humidity	0 to 95%, non-condensing
AC mode BTU / hr. (full load)	671.1
Battery mode BTU / hr. (full load)	1416.7
COMMUNICATIONS	
Communications interface	USB; DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface
Network monitoring port description	Supports detailed monitoring of UPS and site power conditions
PowerAlert software	Included
Communications cable	USB and DB9 cabling included
WatchDog compatibility	Supports Watchdog application, OS and hard-reboot restart options for remote applications
LINE / BATTERY TRANSFER	
Transfer time	4 to 8 milliseconds
Low voltage transfer to battery power (setpoint)	167
High voltage transfer to battery power (setpoint)	260
SPECIAL FEATURES	
Grounding lug	Back panel grounding lug

Cold Start (startup in battery mode during a power failure)	Cold-start operation supported
High availability UPS features	Hot swappable batteries
Green & high efficiency features	Greater than 95% efficiency - GREEN UPS
CERTIFICATIONS	
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Meets FCC Part 15 Category A (EMI)
WARRANTY	
Product Warranty Period (Worldwide)	2-year warranty, 3 year with registration. Note: registration is required for 3-year warranty.
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance

Related Items

Optional Products

Related Model	Description	Qty.
SNMPWEBCARD	For remote monitoring and control via SNMP, Web, or Telnet.	1
ENVIROSENSE	Monitors temperature, humidity and contact-closure inputs. (Requires SNMPWEBCARD or switched PDU.)	1
U022-010	10-ft. USB2.0 A/B Gold Device Cable (A Male to B Male)	1
DTEL2	Network Surge Suppressor - Essential protection for data and communication lines	1
DCATV	Network Surge Suppressor - Essential protection for TV/VCR coaxial lines	1
DNET1	Network Surge Suppressor - Essential protection for data and communication lines	1
WEXT5-5000TEL	5-Year Extended Warranty - For SMART5000TEL3U only	1
2-9USTAND	Enables Tower Placement of Rackmount UPS Systems	1
MODBUSCARD	For remote monitoring and control via MODBUS protocol	1
2POSTRMKITHD	Enables 2-Post Rackmount Installation of 3U and Larger UPS, Transformer and Battery Pack Components	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?variables.txtModelID=3035.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.